

Storing Channels

• Manual Preset

Up to 8 stations can be stored.

1. Push the tuning button to start receiving the station you wish to store.
2. Select 1 control assist button you wish to store on and push until a beep is heard.

The stored station and frequency will be shown onscreen.



• Automatic

Out of the receivable stations, the 8 stations with the best reception can be stored automatically.

1. Push the **選局** control assist button.



2. Push the **オートメモリ** control assist button until a beep is heard.

The screen will indicate that channels are currently being tuned.



3. From now on, when a control assist button is pushed the station stored on that button will be received.

- If battery terminals are removed, memory will be cleared.